

CLEVEREVAC DYNAMIC GREEN & RED X EXIT SIGN



Dynamic LEDs Sequencing Arrow



Illuminated Red X with Side Flashing Red LED's

PRODUCT INFORMATION

| | |
|-----------------------|---|
| Part Number | DYRL-CP-RL-HV |
| MIC | AUA01850010001 |
| Description | L10 Lithium Nanophosphate CleverEVAC Dynamic Green and Red X EXIT sign, with Volt Free (VF) & 24V interface for ON/OFF activation of Dynamic Green & Red X Enhancement |
| Construction | PC/ABS body with PC diffuser |
| Mounting | Ceiling / Wall mounted single sided |
| Dimensions L x W x H | 367mm x 214mm x 80mm |
| Weight | 2.0kg |
| Operating Mode | Maintained – Sequencing arrows or illuminated Red X with side flashing Red LED's activated on VF/24V input trigger and capable of being activated in power-on and battery-backed mode |
| Testing System | Zoneworks XTHIVE (RF) |
| Battery | Lithium Nanophosphate, 3.3V 5000mAh |
| Charging Method | Intelligent current limited constant voltage |
| Diffuser | Pictograph, Two elements (Running Man and Arrow Left) |
| Lamp(s) | LED panel, 100,000 hours |
| Operating Voltage | 240V AC; 50Hz |
| Power Consumption | 1.5 Watts (Standby), 9.0 Watts (Max) |
| IP Rating | IP20 |
| Operating Temperature | 1°C to 40°C |
| AS2293 Classification | C ₀ =E1.6 C ₉₀ =E1.25 |
| Viewing Distance | 24m |

REPLACEMENT PARTS

| PART NUMBER | DESCRIPTION |
|-------------|--|
| 1530230 | BATTERY:L10 3.3V 5AH. 200mm lead.Brkt. |
| 8002925 | PCA: DYxx Driver Board #CT10142-L8 |
| 8003190 | PCA: RF Node CT10678-Ax internal antenna |

Disclaimer: Clevertronics Pty Ltd is a vendor of CleverEVAC products. It is not a fire engineer or designer. It does not purport to recommend its products for use in any particular application or to achieve any particular outcome. Purchasers and users of its products must take their own steps to ensure compliance with statutory requirements, safe practice and suitable application of the products.