

## CLEVEREVAC DYNAMIC GREEN EXIT SIGN (ZONWORKS XTHIVE)



Dynamic LEDs Sequencing Arrow

### PRODUCT INFORMATION

Part Number	DYGL-CP-RL-HV
MIC	
Description	L10 Lithium Nanophosphate CleverEVAC Dynamic Green EXIT sign, with Volt Free (VF) & 24V interface for ON/OFF activation of Dynamic Green Enhancement
Construction	PC/ABS body with PC diffuser
Mounting	Ceiling / Wall mounted single sided
Dimensions L x W x H	367mm x 214mm x 72mm
Weight	2.0kg
Operating Mode	Maintained – Sequencing arrows activated on VF/24V input trigger and capable of being activated in power-on and battery-backed mode
Testing System	Zoneworks XTHIVE (RF)
Battery	Lithium Nanophosphate, 3.2V 2500mAh
Charging Method	Intelligent current limited constant voltage
Diffuser	Pictograph, Single element (Running Man and Arrow Right)
Lamp(s)	LED panel, 100,000 hours
Operating Voltage	240V AC; 50Hz
Power Consumption	1.5 Watts (Standby), 5.0 Watts (Max)
IP Rating	IP20
Operating Temperature	1°C to 40°C
AS2293 Classification	C <sub>0</sub> =E1.25 C <sub>90</sub> =B1.25 C <sub>180</sub> =A1
Viewing Distance	24m

### REPLACEMENT PARTS

PART NUMBER	DESCRIPTION
1530030	BATTERY:L10 3.3V 2.5AH 260mm lead,noBRKT
8002925	PCA: DYxx Driver Board #CT10142-L8
8003190	PCA: RF Node CT10678-Ax internal antenna

**Disclaimer:** Clevertronics Pty Ltd is a vendor of CleverEVAC products. It is not a fire engineer or designer. It does not purport to recommend its products for use in any particular application or to achieve any particular outcome. Purchasers and users of its products must take their own steps to ensure compliance with statutory requirements, safe practice and suitable application of the products.